

TAO-A.V-MXN5

TAO-A.V Option Switch Settings: 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill MXN 20, 50, 100, 200, 500 5bills.

TAO-A.V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject MXN 20	ON											
	Accept MXN 20	OFF											
★	Reject MXN 50		ON										
★	Accept MXN 50		OFF										
★	Reject MXN 100			ON									
★	Accept MXN 100			OFF									
★	Reject MXN 200				ON								
★	Accept MXN 200				OFF								
★	Reject MXN 500					ON							
★	Accept MXN 500					OFF							
★	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable						ON						
★	Harness Enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulses / MXN 10								OFF	OFF			
	2 pulses / MXN 10								ON	OFF			
	5 pulses / MXN 10								OFF	ON			
	10 pulses / MXN 10								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Default setting

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) MDB : Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2

TAO-A.V-MXN5(Pulse/ICT104U/ICT104V/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104V Interface		OFF	ON	
	ICT104U Interface		OFF	OFF	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	ICT	Pulse	MDB
BV1	MXN 20	MXN 20	MXN 20
BV2	MXN 50	MXN 50	MXN 50
BV3	MXN 100	MXN 100	MXN 100
BV4	MXN 200	MXN 200	MXN 200
BV5	MXN 500	MXN 500	MXN 500

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104V Interface		OFF	ON	
★	ICT104U Interface		OFF	OFF	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104V Interface		OFF	ON	
	ICT104U Interface		OFF	OFF	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

TAO-V-MXN5

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT104V Interface		OFF	ON	
	ICT104U Interface		OFF	OFF	
★	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting