

TAO-V-VND6

TAO-V Option Switch Settings: 1(Pulse/ICT/MDB/ICT104V)

Supported bill đ 1000, 2000, 5000, 10000, 20000, 50000 6bills.

TAO-V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject đ 1000	ON											
	Accept đ 1000	OFF											
★	Reject đ 2000		ON										
	Accept đ 2000		OFF										
★	Reject đ 5000			ON									
	Accept đ 5000			OFF									
★	Reject đ 10000				ON								
	Accept đ 10000				OFF								
★	Reject đ 20000					ON							
	Accept đ 20000					OFF							
★	Reject đ 50000						ON						
	Accept đ 50000						OFF						
★	Harness Disable							ON					
	Harness Enable							OFF					
★	Inhibit Active High								ON				
	Inhibit Active Low								OFF				
★	1 pulse / đ 1000									OFF	OFF		
	5 pulses / đ 1000									ON	OFF		
	10 pulses / đ 1000									OFF	ON		
	20 pulses / đ 1000									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off								OFF	OFF		
		60ms on / 300ms off								ON	OFF		
		30ms on / 50ms off								OFF	ON		
		150ms on / 150ms off								ON	ON		

★ Manufacture setting

◆ Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

TAO-V-VND6

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	đ 1000	đ 1000	đ 1000
BV2	đ 2000	đ 2000	đ 2000
BV3	đ 5000	đ 5000	đ 5000
BV4	đ 10000	đ 10000	đ 10000
BV5	đ 20000	đ 20000	đ 20000
BV6	đ 50000	đ 50000	đ 50000

Interface Settings: 2(ICT/104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Not Used	ON			
	Not Used	OFF			
	Pulse Mode		ON	OFF	
★	ICT Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

TAO-V-VND6

TAO-V Option Switch Settings: 1(Pulse/ICT/MDB/ICT104V)

Supported bill ₹ 1000, 2000, 5000, 10000, 20000, 50000 6bills.

TAO-V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject ₹ 1000	ON											
★	Accept ₹ 1000	OFF											
	Reject ₹ 2000		ON										
★	Accept ₹ 2000		OFF										
	Reject ₹ 5000			ON									
★	Accept ₹ 5000			OFF									
	Reject ₹ 10000				ON								
★	Accept ₹ 10000				OFF								
	Reject ₹ 20000					ON							
★	Accept ₹ 20000					OFF							
	Reject ₹ 50000						ON						
★	Accept ₹ 50000						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / ₹ 1000									OFF	OFF		
	5 pulses / ₹ 1000									ON	OFF		
	10 pulses / ₹ 1000									OFF	ON		
	20 pulses / ₹ 1000									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off									OFF	OFF	
		60ms on / 300ms off									ON	OFF	
		30ms on / 50ms off									OFF	ON	
		150ms on / 150ms off									ON	ON	

★ Manufacture setting

◆ Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

TAO-V-VND6

TAO-V Option Switch Settings: 1(Pulse/ICT/MDB/ICT104V)

Supported bill ₹ 1000, 2000, 5000, 10000, 20000, 50000 6bills.

TAO-V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject ₹ 1000	ON											
★	Accept ₹ 1000	OFF											
	Reject ₹ 2000		ON										
★	Accept ₹ 2000		OFF										
	Reject ₹ 5000			ON									
★	Accept ₹ 5000			OFF									
	Reject ₹ 10000				ON								
★	Accept ₹ 10000				OFF								
	Reject ₹ 20000					ON							
★	Accept ₹ 20000					OFF							
	Reject ₹ 50000						ON						
★	Accept ₹ 50000						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / ₹ 1000									OFF	OFF		
	5 pulses / ₹ 1000									ON	OFF		
	10 pulses / ₹ 1000									OFF	ON		
	20 pulses / ₹ 1000									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off									OFF	OFF	
		60ms on / 300ms off									ON	OFF	
		30ms on / 50ms off									OFF	ON	
		150ms on / 150ms off									ON	ON	

★ Manufacture setting

◆ Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

TAO-V-VND6

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	₫ 1000	₫ 1000	₫ 1000
BV2	₫ 2000	₫ 2000	₫ 2000
BV3	₫ 5000	₫ 5000	₫ 5000
BV4	₫ 10000	₫ 10000	₫ 10000
BV5	₫ 20000	₫ 20000	₫ 20000
BV6	₫ 50000	₫ 50000	₫ 50000

TAO-V-VND6

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	₫ 1000	₫ 1000	₫ 1000
BV2	₫ 2000	₫ 2000	₫ 2000
BV3	₫ 5000	₫ 5000	₫ 5000
BV4	₫ 10000	₫ 10000	₫ 10000
BV5	₫ 20000	₫ 20000	₫ 20000
BV6	₫ 50000	₫ 50000	₫ 50000

Interface Settings: 2(ICT/104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Not Used	ON			
	Not Used	OFF			
	Pulse Mode		ON	OFF	
★	ICT Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Not Used	ON			
	Not Used	OFF			
	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT/104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Not Used	ON			
	Not Used	OFF			
	Pulse Mode		ON	OFF	
★	ICT Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Not Used	ON			
	Not Used	OFF			
	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting