

V7-KZT3

V7 Option Switch Settings: 1 (Pulse/ICT004U/MDB)

Supported bill KZT 200, 500, 1000 3bills.

V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
★ Reject KZT 200	ON							
★ Accept KZT 200	OFF							
★ Reject KZT 500		ON						
★ Accept KZT 500		OFF						
★ Reject KZT 1000			ON					
★ Accept KZT 1000			OFF					
★ Reserved				ON				
★ Reserved				OFF				
★ Reserved					ON			
★ Reserved					OFF			
★ Reserved						ON		
★ Reserved						OFF		
★ Harness Disable							ON	
★ Harness Engble							OFF	
★ Inhiblit Active High								ON
★ Inhibit Active Low								OFF

◆ Factory configuration has all switches in the OFF position.

V7 Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ 1 pulse / KZT 100	OFF	OFF		
2 pulse / KZT 100	ON	OFF		
4 pulse / KZT 100	OFF	ON		
20 pulse / KZT 100	ON	ON		
★ 50ms LO / 50ms HI			OFF	OFF
60ms LO / 300ms HI			ON	OFF
30ms LO / 50ms HI			OFF	ON
150ms LO / 150ms HI			ON	ON

★ Manufacture setting

V7-KZT3(Pulse/ICT004U/MDB)

V7 Interface Settings: 3 (ICT)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
★ ICT Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

V7 Interface Settings: 3 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
ICT Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ MDB Interface		OFF	OFF	
ICT Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	KZT 200	KZT 200	KZT 200
BV2	KZT 500	KZT 500	KZT 500
BV3	KZT 1000	KZT 1000	KZT 1000

Note: 1.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.
2.Remove the front cover and the dip-switch in on the CPU board.
(Please refer to "Sw1" setting.)