

V7-RSD7

V7 Option Switch Settings:1(Pulse/C.C.Talk)

Supported bill RSD 10, 20, 50, 100, 200, 500, 1000 7bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject RSD 10 & 20	ON											
★	Accept RSD 10 & 20	OFF											
	Reject RSD 50 & 100		ON										
★	Accept RSD 50 & 100		OFF										
	Reject RSD 200			ON									
★	Accept RSD 200			OFF									
	Reject RSD 500				ON								
★	Accept RSD 500				OFF								
	Reject RSD 1000					ON							
★	Accept RSD 1000					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / RSD 10									OFF	OFF		
	5 pulses / RSD 10									ON	OFF		
	10 pulses / RSD 10									OFF	ON		
	25 pulses / RSD 10									ON	ON		
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) CCTalk Parameters Restore Switch Put this switch to on and reset power will restore the CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

V7-RSD7(Pulse/C.C.Talk)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	CCTalk Interface Mode		OFF		
	Reserved			ON	
★				OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	C.C.Talk	Pulse
BV1	10	10
BV2	20	20
BV3	50	50
BV4	100	100
BV5	200	200
BV6	500	500
BV7	1000	1000

Interface Settings: 2(C.C.Talk)

	INTERFACE	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
	Pulse Mode		ON		
★	CCTalk Interface Mode		OFF		
	CCTalk Parameters Restore Switch (Please see Note.3 for detail(CCTalk only)			ON	
★	Reserved			OFF	
	Decrypt MODE				ON
★	Encryption MODE				OFF

★ Manufacture setting

Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) CCTalk Parameters Restore Switch Put this switch to on and reset power will restore the CCTalk address to its default value of 40 and the encryption key to its default value of 123456.