

## V7E/LX7-JMD6

### V7E/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/ MDB)

Supported bill JMD 50, 100, 500, 1000, 2000, 5000 6bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	
★ Reject JMD 50	ON												
★ Accept JMD 50	OFF												
★ Reject JMD 100		ON											
★ Accept JMD 100		OFF											
★ Reject JMD 500			ON										
★ Accept JMD 500			OFF										
★ Reject JMD 1000				ON									
★ Accept JMD 1000				OFF									
★ Reject JMD 5000					ON								
★ Accept JMD 5000					OFF								
★ Reject JMD 2000						ON							
★ Accept JMD 2000						OFF							
<b>Pulse Mode</b>	<b>Other Mode</b>												
★ Harness Disable	BA stopped working when fishing							ON					
★ Harness Enable	Normal							OFF					
★ Inhibit Active High								ON					
★ Inhibit Active Low								OFF					
★ 1 pulse / JMD 50 & 100	(Note.3)								OFF	OFF			
★ 2 pulses / JMD 50 & 100	(Note.3)								ON	OFF			
★ 4 pulses / JMD 50 & 100	(Note.3)								OFF	ON			
★ 20 pulses / JMD 50 & 100	(Note.3)								ON	ON			
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF			
	60ms LO / 300ms HI								ON	OFF			
	30ms LO / 50ms HI								OFF	ON			
	150ms LO / 150ms HI								ON	ON			

★ Manufacture Default setting

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Pulse Mode:

When Dip 1 is OFF, One Pulse per JMD 50

When Dip 1 is ON ,One Pulse per JMD 100

**Appendix**

## V7E/LX7-JMD6(Pulse/ICT104V/ICT104U/ MDB)

### DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

Interface Bill value	ICT104V	ICT104U	Pulse	MDB
BV1	JMD 50	JMD 50	JMD 50	JMD 50
BV2	JMD 100	JMD 100	JMD 100	JMD 100
BV3	JMD 500	JMD 500	JMD 500	JMD 500
BV4	JMD 1000	JMD 1000	JMD 1000	JMD 1000
BV5	JMD 5000	JMD 5000	JMD 5000	JMD 5000
BV6	JMD 2000	JMD 2000	JMD 2000	JMD 2000

### DIP SWITCHES SETTING : 2( ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

### DIP SWITCHES SETTING : 2( ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

### DIP SWITCHES SETTING : 2( MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
MDB Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Note 1. Please reset the bill acceptor after any changes on Dip switch.

2. Dip Switch 1 to 5 are only for Pulse mode.