

BRV-KUR6(KHR4+USD2)

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy/MDB Dummy)

Supported bill KHR 1000, 2000, 5000, 10000 4bills.
USD 1, 5 2bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject KHR 1000	ON											
★ Accept KHR 1000	OFF											
★ Reject KHR 2000		ON										
★ Accept KHR 2000		OFF										
★ Reject KHR 5000			ON									
★ Accept KHR 5000			OFF									
★ Reject KHR 10000				ON								
★ Accept KHR 10000				OFF								
★ Reject USD 1 & 5					ON							
★ Accept USD 1 & 5					OFF							
★ Normal						OFF	OFF					
Load Banknote to Recycle						ON	OFF					
Disable Recycler Function						OFF	ON					
Unload Banknote to Stacker						ON	ON					
Reserved									ON			
★ Reserved												OFF
MDB Mode	SW1	SW2	SW3	SW4	JPSTD Dummy Mode							
Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★ Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★ Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
Reserved			ON		4 Bank Note Limitation Per Transaction	ON	ON	OFF				
★ Reserved			OFF		5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
Reserved				ON	6 Bank Note Limitation Per Transaction	ON	OFF	ON				
★ Reserved				OFF	7 Bank Note Limitation Per Transaction	OFF	ON	ON				
Virtual MDB Recycler Function	(Note.4)			ON	No Refund After the Deal							ON
★ Standard MDB Recycler Function				OFF	★ Refund After the Deal							OFF

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses ,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibrate card is needed.

(4) Recycled Banknote represents virtual MDB coin type.

(5) Normal:Scaling Factor (SF) = 1

Decimal Point Position (DPP) = 0

(6) The function(credit divide by1000) is used at standard MDB recycler mode

(7) The credit divide by 1000 on JPSTD Dummy Mode.

(8) USD 1=KHR 4000, USD 5=KHR 20000.

Appendix

BRV-KUR6(KHR4+USD2)(ICT-BC/MDB/JPSTD Dummy/MDB Dummy)

Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
Reserved	ON			
★ Reserved	OFF			
Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
MDB Dummy Mode			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

INTERFACE	SW5	SW6	SW7	SW8
Escrow (JPSTD Dummy Mode)	ON			
★ No Escrow (JPSTD Dummy Mode)	OFF			
Reserved		ON		
★ Reserved		OFF		
MDB Mode			OFF	OFF
★ JPSTD Dummy Mode	(Note.7)		OFF	ON
MDB Dummy Mode			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Normal Credit (Note.5)	ON			
Credit divide by 1000 (Note.6)	OFF			
Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
MDB Dummy Mode			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB Dummy)

INTERFACE	SW5	SW6	SW7	SW8
★ Normal Credit (Note.5)	ON			
Credit divide by 1000 (Note.6)	OFF			
Reserved		ON		
★ Reserved		OFF		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
★ MDB Dummy Mode			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB (Dummy)	Recycler banknote inventory	
BV1	KHR 1000	KHR 1000	KHR 1000	KHR 1000	35 pcs
BV2	KHR 2000	KHR 2000	KHR 2000	KHR 2000	35 pcs
BV3	KHR 5000	KHR 5000	KHR 5000	KHR 5000	35 pcs
BV4	KHR 10000	KHR 10000	KHR 10000	KHR 10000	30 pcs
BV5	USD 1	USD 1	USD 1	USD 1	30 pcs
BV6	USD 5	USD 5	USD 5	USD 5	30 pcs