

L77F/PL77-BWP3

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill BWP 10, 20, 50 3bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / BWP 10	OFF	OFF	OFF							
2 Pulses / BWP 10	OFF	OFF	ON							
3 Pulses / BWP 10	OFF	ON	OFF							
4 Pulses / BWP 10	OFF	ON	ON							
5 Pulses / BWP 10	ON	OFF	OFF							
10 Pulses / BWP 10	ON	OFF	ON							
20 Pulses / BWP 10	ON	ON	OFF							
100 Pulses / BWP 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept BWP 10						ON				
Reject BWP 10						OFF				
★ Accept BWP 20							ON			
Reject BWP 20							OFF			
★ Accept BWP 50								ON		
Reject BWP 50								OFF		
★ Reserved									ON	
Reserved									OFF	
★ Reserved										ON
Reserved										OFF

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

L77F/PL77-BWP3(Pulse/ICT104U/IC104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
★ MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	BWP 10	BWP 10	BWP 10	BWP 10
BV2	BWP 20	BWP 20	BWP 20	BWP 20
BV3	BWP 50	BWP 50	BWP 50	BWP 50

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting