

# L77F/PL77-JOD4

## L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/MDB/ICT104U/ICT104V)

Supported bill JOD 1, 5, 10, 20 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / JOD 1	OFF	OFF	OFF							
2 Pulses / JOD 1	OFF	OFF	ON							
3 Pulses / JOD 1	OFF	ON	OFF							
4 Pulses / JOD 1	OFF	ON	ON							
5 Pulses / JOD 1	ON	OFF	OFF							
10 Pulses / JOD 1	ON	OFF	ON							
20 Pulses / JOD 1	ON	ON	OFF							
100 Pulses / JOD 1	ON	ON	ON							
★ Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept JOD 1						ON				
★ Reject JOD 1						OFF				
★ Accept JOD 5							ON			
★ Reject JOD 5							OFF			
★ Accept JOD 10								ON		
★ Reject JOD 10								OFF		
★ Accept JOD 20									ON	
★ Reject JOD 20									OFF	
★ Reserved										ON
★ Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

# L77F/PL77-JOD4(Pulse/MDB/ICT104U/ICT104V)

## DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 1000 Decimal Point Position (DPP) = 3	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	JOD 1	JOD 1	JOD 1	JOD 1
BV2	JOD 5	JOD 5	JOD 5	JOD 5
BV3	JOD 10	JOD 10	JOD 10	JOD 10
BV4	JOD 20	JOD 20	JOD 20	JOD 20

## DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting