

L77F/PL77-MAD4

L77F/PL77 Option Switch Settings : 1(Pulse/ICT104U/MDB/ccTalk)

Supported bill MAD 20, 50, 100, 200 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / MAD 10	OFF	OFF	OFF							
2 Pulses / MAD 10	OFF	OFF	ON							
3 Pulses / MAD 10	OFF	ON	OFF							
4 Pulses / MAD 10	OFF	ON	ON							
5 Pulses / MAD 10	ON	OFF	OFF							
10 Pulses / MAD 10	ON	OFF	ON							
20 Pulses / MAD 10	ON	ON	OFF							
100 Pulses / MAD 10	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept MAD 20						ON				
Reject MAD 20						OFF				
★ Accept MAD 50							ON			
Reject MAD 50							OFF			
★ Accept MAD 100								ON		
Reject MAD 100								OFF		
★ Accept MAD 200									ON	
Reject MAD 200									OFF	
★ Reserved										ON
Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip Switch 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L77F/PL77-MAD4(Pulse/ICT104U/MDB/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
MDB Mode		ON	ON	OFF
★ Pulse Mode		ON	OFF	OFF
ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
MDB Mode		ON	ON	OFF
Pulse Mode		ON	OFF	OFF
★ ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ MDB Mode		ON	ON	OFF
Pulse Mode		ON	OFF	OFF
ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch (Please see Nota.3 for Detail)		OFF	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ccTalk	ICT104U	Pulse	MDB
BV1	MAD 20	MAD 20	MAD 20	MAD 20
BV2	MAD 50	MAD 50	MAD 50	MAD 50
BV3	MAD 100	MAD 100	MAD 100	MAD 100
BV4	MAD 200	MAD 200	MAD 200	MAD 200