

L77F/PL77-MNT4

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill MNT 1000, 5000, 10000, 20000 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / MNT 1000	OFF	OFF	OFF							
2 Pulses / MNT 1000	OFF	OFF	ON							
3 Pulses / MNT 1000	OFF	ON	OFF							
4 Pulses / MNT 1000	OFF	ON	ON							
5 Pulses / MNT 1000	ON	OFF	OFF							
10 Pulses / MNT 1000	ON	OFF	ON							
20 Pulses / MNT 1000	ON	ON	OFF							
100 Pulses / MNT 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept MNT 1000						ON				
Reject MNT 1000						OFF				
★ Accept MNT 5000							ON			
Reject MNT 5000							OFF			
★ Accept MNT 10000								ON		
Reject MNT 10000								OFF		
★ Accept MNT 20000									ON	
Reject MNT 20000									OFF	
★ Reserved										ON
★ Reserved										OFF

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

L77F/PL77-MNT4(Pulse/ICT104U/IC104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
★ MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	MNT 1000	MNT 1000	MNT 1000	MNT 1000
BV2	MNT 5000	MNT 5000	MNT 5000	MNT 5000
BV3	MNT 10000	MNT 10000	MNT 10000	MNT 10000
BV4	MNT 20000	MNT 20000	MNT 20000	MNT 20000

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting