

L83-CEK9(CZK5+EUR4)

L83-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ccTalk/Parallel A5)

Supported bill Kč 100, 200, 500, 1000, 2000

€ 5, 10, 20, 50 9 bills.

(With stacker):Kč 100, 200, 500, 1000

€ 5, 10, 20, 50 8 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Kč 100 & € 5	OFF	OFF	OFF							
2 Pulses / Kč 100 & € 5	OFF	OFF	ON							
3 Pulses / Kč 100 & € 5	OFF	ON	OFF							
4 Pulses / Kč 100 & € 5	OFF	ON	ON							
5 Pulses / Kč 100 & € 5	ON	OFF	OFF							
10 Pulses / Kč 100 & € 5	ON	OFF	ON							
20 Pulses / Kč 100 & € 5	ON	ON	OFF							
100 Pulses / Kč 100 & € 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Kč 100, 200, 500, 1000						ON				
Reject Kč 100, 200, 500, 1000						OFF				
★ Accept Kč 2000							ON			
Reject Kč 2000							OFF			
★ Accept € 5, 10								ON		
Reject € 5, 10								OFF		
★ Accept € 20									ON	
Reject € 20									OFF	
★ Accept € 50										ON
Reject € 50										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456..

L83-CEK9(CZK5+EUR4)(Pulse/ccTalk/Parallel A5)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
cctalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
Parallel A5 Compatible Mode		ON	ON	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ CRC 16-bit checksum	ON			
8-bit checksum	OFF			
Pulse Mode		ON	OFF	
★ cctalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
Parallel A5 Compatible Mode		ON	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(Parallel A5)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
cctalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★ Parallel A5 Compatible Mode		ON	ON	
Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ccTalk	Parallel A5
BV1			
BV2	Kč 100	Kč 100	Kč 100
BV3	Kč 200	Kč 200	Kč 200
BV4	Kč 500	Kč 500	Kč 500
BV5	Kč 1000	Kč 1000	Kč 1000
BV6	€ 5	€ 5	€ 5
BV7	€ 10	€ 10	€ 10
BV8	€ 20	€ 20	€ 20
BV9	€ 50	€ 50	€ 50
BV10	Kč 2000	Kč 2000	Kč 2000