

L83-GHS6

L83 Option Switch Settings : 1(Pulse/RS232 A0/ccTalk/ICT104U)

Supported bill GHS 5, 10, 20, 50, 100, 200 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★ 1 Pulse / GHS 1	OFF	OFF	OFF								
2 Pulses / GHS 1	OFF	OFF	ON								
3 Pulses / GHS 1	OFF	ON	OFF								
4 Pulses / GHS 1	OFF	ON	ON								
5 Pulses / GHS 1	ON	OFF	OFF								
10 Pulses / GHS 1	ON	OFF	ON								
20 Pulses / GHS 1	ON	ON	OFF								
100 Pulses / GHS 1	ON	ON	ON								
Fast output Pulse Lo= 50ms Hi=100ms											ON
★ Slow output Pulse Lo= 50ms Hi=300ms											OFF
Inhibit level Active Low					ON						
★ Inhibit level Active High					OFF						
★ Accept GHS 5						ON					
Reject GHS 5						OFF					
★ Accept GHS 10							ON				
Reject GHS 10							OFF				
★ Accept GHS 20 & 50								ON			
Reject GHS 20 & 50								OFF			
★ Accept GHS 100									ON		
Reject GHS 100									OFF		
★ Accept GHS 200										ON	
Reject GHS 200										OFF	

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

Note.3 Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L83-GHS6(Pulse/RS232 A0/ccTalk/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
RS232 A0 Mode		ON	ON	OFF
★ Pulse Mode		ON	OFF	OFF
ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
RS232 A0 Mode		ON	ON	OFF
Pulse Mode		ON	OFF	OFF
★ ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
★ RS232 A0 Mode		ON	ON	OFF
Pulse Mode		ON	OFF	OFF
ICT104U Mode		ON	OFF	ON

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	GHS 5
4	GHS 10
5	GHS 20
6	GHS 50
7	GHS 100
8	GHS 200
9	Reserved

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
Encryption Mode				ON
★ Decrypt Mode				OFF

★ Manufacture setting

Note.3 Turn this dip to with restart the bill acceptor will restore

ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccTalk	ICT104U
BV1	Reserved	Reserved	Reserved	Reserved
BV2	Reserved	Reserved	Reserved	Reserved
BV3	GHS 5	GHS 5	GHS 5	GHS 5
BV4	GHS 10	GHS 10	GHS 10	GHS 10
BV5	GHS 20	GHS 20	GHS 20	GHS 20
BV6	GHS 50	GHS 50	GHS 50	GHS 50
BV7	GHS 100	GHS 100	GHS 100	GHS 100
BV8	GHS 200	GHS 200	GHS 200	GHS 200