

L83-MAD4

L83-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ccTalk/Parallel A5)

Supported bill MAD 20, 50, 100, 200 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / MAD 10	OFF	OFF	OFF							
2 Pulse / MAD 10	OFF	OFF	ON							
3 Pulse / MAD 10	OFF	ON	OFF							
4 Pulse / MAD 10	OFF	ON	ON							
5 Pulse / MAD 10	ON	OFF	OFF							
10 Pulse / MAD 10	ON	OFF	ON							
20 Pulse / MAD 10	ON	ON	OFF							
100 Pulse / MAD 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept MAD 20						ON				
Reject MAD 20						OFF				
★ Accept MAD 50							ON			
Reject MAD 50							OFF			
★ Accept MAD 100								ON		
Reject MAD 100								OFF		
★ Accept MAD 200									ON	
Reject MAD 200									OFF	
★ Reserved										ON
Reserved										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L83-MAD4(Pulse/ccTalk/Parallel A5)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(Parallel A5)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Parallel A5 Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ccTalk	Parallel A5
BV1	20	20	20
BV2	50	50	50
BV3	100	100	100
BV4	200	200	200