

L83-PLN5+EUR4

L83-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ccTalk/Parallel A5)

Supported bill zloty 10, 20, 50, 100, 200

€ 5, 10, 20, 50 9 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / zloty 5 & € 1	OFF	OFF	OFF							
2 Pulses / zloty 5 & € 1	OFF	OFF	ON							
3 Pulses / zloty 5 & € 1	OFF	ON	OFF							
4 Pulses / zloty 5 & € 1	OFF	ON	ON							
5 Pulses / zloty 5 & € 1	ON	OFF	OFF							
10 Pulses / zloty 5 & € 1	ON	OFF	ON							
20 Pulses / zloty 5 & € 1	ON	ON	OFF							
100 Pulses / zloty 5 & € 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept zloty 10 & 20						ON				
Reject zloty 10 & 20						OFF				
★ Accept zloty 50 & 100							ON			
Reject zloty 50 & 100							OFF			
★ Accept zloty 200								ON		
Reject zloty 200								OFF		
★ Accept € 5 & 10 & 20									ON	
Reject € 5 & 10 & 20									OFF	
★ Accept € 50										ON
Reject € 50										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456..

L83-PLN9(Pulse/ccTalk/Parallel A5)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
cctalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
Parallel A5 Mode		ON	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ cctalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
Parallel A5 Mode		ON	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(Parallel A5)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
cctalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
Parallel A5 Mode		ON	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ccTalk	Parallel A5
BV1	zloty 10	zloty 10	zloty 10
BV2	zloty 20	zloty 20	zloty 20
BV3	zloty 50	zloty 50	zloty 50
BV4	zloty 100	zloty 100	zloty 100
BV5	zloty 200	zloty 200	zloty 200
BV6	€ 5	€ 5	€ 5
BV7	€ 10	€ 10	€ 10
BV8	€ 20	€ 20	€ 20
BV9	€ 50	€ 50	€ 50