

L83-UAH9

L83/P3/P6 DIP SWITCHES SETTING : 1(Pulse/ccTalk/Parallel A5)

Supported bill HRYVEN 1, 2, 5, 10, 20, 50, 100, 200, 500 9bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / HRYVEN 1 & 5 <small>(Note.3)</small>	OFF	OFF	OFF							
★ 2 Pulses / HRYVEN 1 & 5 <small>(Note.3)</small>	OFF	OFF	ON							
★ 3 Pulses / HRYVEN 1 & 5 <small>(Note.3)</small>	OFF	ON	OFF							
★ 4 Pulses / HRYVEN 1 & 5 <small>(Note.3)</small>	OFF	ON	ON							
★ 5 Pulses / HRYVEN 1 & 5 <small>(Note.3)</small>	ON	OFF	OFF							
★ 10 Pulses / HRYVEN 1 & 5 <small>(Note.3)</small>	ON	OFF	ON							
★ 20 Pulses / HRYVEN 1 & 5 <small>(Note.3)</small>	ON	ON	OFF							
★ 100 Pulses / HRYVEN 1 & 5 <small>(Note.3)</small>	ON	ON	ON							
★ Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
★ Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept HRYVEN 1 & 2 <small>(Note.3)</small>						ON				
★ Reject HRYVEN 1 & 2 <small>(Note.3)</small>						OFF				
★ Accept HRYVEN 5 & 10 & 20 & 50							ON			
★ Reject HRYVEN 5 & 10 & 20 & 50							OFF			
★ Accept HRYVEN 100 & 200								ON		
★ Reject HRYVEN 100 & 200								OFF		
★ Accept HRYVEN 500									ON	
★ Reject HRYVEN 500									OFF	
★ Simulation Bill Box Has Been Removed										ON
★ Default										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Pulse Mode:

Dip 6 turn ON ,One Pulse per HRYVEN 1.

Dip 6 turn OFF,One Pulse per HRYVEN 5.

(4) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L83-UAH9(Pulse/ccTalk/Parallel A5)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
Parallel A5 Mode		ON	ON	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ CRC 16-bit checksum	ON			
8-bit checksum	OFF			
Pulse Mode		ON	OFF	
★ cctalk Interface		OFF	OFF	
Parallel A5 Mode		ON	ON	
ccTalk Parameters Restore Switch (Please see Note for Detail)		OFF	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(Parallel A5)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
cctalk Interface		OFF	OFF	
★ Parallel A5 Mode		ON	ON	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse		Parallel A5	ccTalk
	Dip 6 is ON	Dip 6 is OFF		
BV1	HRYPEN 1	HRYPEN 5	HRYPEN 1	HRYPEN 1
BV2	HRYPEN 2	HRYPEN 10	HRYPEN 2	HRYPEN 2
BV3	HRYPEN 5	HRYPEN 20	HRYPEN 5	HRYPEN 5
BV4	HRYPEN 10	HRYPEN 50	HRYPEN 10	HRYPEN 10
BV5	HRYPEN 20	HRYPEN 100	HRYPEN 20	HRYPEN 20
BV6	HRYPEN 50	HRYPEN 200	HRYPEN 50	HRYPEN 50
BV7	HRYPEN 100	HRYPEN 500	HRYPEN 100	HRYPEN 100
BV8	HRYPEN 200		HRYPEN 200	HRYPEN 200
BV9	HRYPEN 500		HRYPEN 500	HRYPEN 500