

## V7P-FJD6

### V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill FJD 5, 7, 10, 20, 50, 100 6bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject FJD 5 & 7	ON											
★ Accept FJD 5 & 7	OFF											
★ Reject FJD 10		ON										
★ Accept FJD 10		OFF										
★ Reject FJD 20			ON									
★ Accept FJD 20			OFF									
★ Reject FJD 50				ON								
★ Accept FJD 50				OFF								
★ Reject FJD 100					ON							
★ Accept FJD 100					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ <b>Pulse Mode</b>												
★ 1 pulse / FJD 1								OFF	OFF			
2 pulses / FJD 1								ON	OFF			
5 pulses / FJD 1								OFF	ON			
10 pulses / FJD 1								ON	ON			
★ Interface Timing Conversion										OFF	OFF	
		50ms LO / 50ms HI								ON	OFF	
		60ms LO / 300ms HI								OFF	ON	
		30ms LO / 50ms HI								ON	ON	
		150ms LO / 150ms HI								ON	ON	

★ Manufacture setting

Note :

- 1.Default setting.
- 2.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.
- 3.Remove the front cover and the dip-switch in on the CPU board.
- 4.Calibrate card is needed.

## V7P-FJD6(Pulse/ICT104V/ICT104U/MDB)

### Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	Pulse	MDB	ICT104V	ICT104U
BV1	FJD 5	FJD 5	FJD 5	FJD 5
BV2	FJD 7	FJD 7	FJD 7	FJD 7
BV3	FJD 10	FJD 10	FJD 10	FJD 10
BV4	FJD 20	FJD 20	FJD 20	FJD 20
BV5	FJD 50	FJD 50	FJD 50	FJD 50
BV6	FJD 100	FJD 100	FJD 100	FJD 100

### Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting