

# V7P-SAR5

## V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

### Supported bill SAR 1, 5, 10, 50, 100 5bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject SAR 1	ON											
★ Accept SAR 1	OFF											
★ Reject SAR 5		ON										
★ Accept SAR 5		OFF										
★ Reject SAR 10			ON									
★ Accept SAR 10			OFF									
★ Reject SAR 50				ON								
★ Accept SAR 50				OFF								
★ Reject SAR 100					ON							
★ Accept SAR 100					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
<b>Pulse Mode</b>												
★ 1 pulse / SAR 1									OFF	OFF		
2 pulses / SAR 1									ON	OFF		
4 pulses / SAR 1									OFF	ON		
20 pulses / SAR 1									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
	60ms LO / 300ms HI									ON	OFF	
	30ms LO / 50ms HI									OFF	ON	
	150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note :

1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

# V7P-SAR5(Pulse/ICT104V/ICT104U/MDB)

## Interface Settings: 2(Pulse)

## Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	Pulse	MDB	ICT104V	ICT104U
BV1	SAR 1	SAR 1	SAR 1	SAR 1
BV2	SAR 5	SAR 5	SAR 5	SAR 5
BV3	SAR 10	SAR 10	SAR 10	SAR 10
BV4	SAR 50	SAR 50	SAR 50	SAR 50
BV5	SAR100	SAR100	SAR100	SAR100

## Interface Settings: 2(ICT104U)

## Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

## Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting