

XBA mini-LAK8

XBA mini Option Switch Settings: 1(Pulse/MDB/ICT104V/ICT104U)

Supported bill LAK 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 8bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	
★	Reject LAK 500 & 1000	ON												
★	Accept LAK 500 & 1000	OFF												
	Reject LAK 2000 & 5000		ON											
★	Accept LAK 2000 & 5000		OFF											
	Reject LAK 10000 & 20000			ON										
★	Accept LAK 10000 & 20000			OFF										
	Reject LAK 50000				ON									
★	Accept LAK 50000				OFF									
	Reject LAK 100000					ON								
★	Accept LAK 100000					OFF								
	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON							
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF							
	Stack Banknote when Power-up							ON						
★	Reject Banknote when Power-up							OFF						
	Reserved								ON					
★	Reserved								OFF					
	Inhibit Active High									ON				
★	Inhibit Active Low									OFF				
	Reserved										ON			
★	Reserved										OFF			
★	Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF		
		60ms LO / 300ms HI									ON	OFF		
		30ms LO / 50ms HI									OFF	ON		
		150ms LO / 150ms HI									ON	ON		

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Calibration card is needed.

XBA mini-LAK8(Pulse/MDB/ICT104V/ICT104U)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / LAK 500			OFF	OFF
	2 pulses / LAK 500			OFF	ON
	5 pulses / LAK 500			ON	OFF
	10 pulses / LAK 500			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Connect with coin changer	ON			
	Connect with ICT JPSTD converter board	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
★	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(Other)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	500	500	500	500
BV2	1000	1000	1000	1000
BV3	2000	2000	2000	2000
BV4	5000	5000	5000	5000
BV5	10000	10000	10000	10000
BV6	20000	20000	20000	20000
BV7	50000	50000	50000	50000
BV8	100000	100000	100000	100000

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 1	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting