

XBA mini-PHP6

XBA mini Option Switch Settings: 1(Pulse/MDB/ICT104U/ICT104V)

Supported bill PHP 20, 50, 100, 200, 500, 1000 6bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject PHP 20	ON											
★ Accept PHP 20	OFF											
★ Reject PHP 50		ON										
★ Accept PHP 50		OFF										
★ Reject PHP 100			ON									
★ Accept PHP 100			OFF									
★ Reject PHP 200				ON								
★ Accept PHP 200				OFF								
★ Reject PHP 500 & 1000					ON							
★ Accept PHP 500 & 1000					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Stack Banknote when Power-up							ON					
★ Reject Banknote when Power-up							OFF					
★ Reserved								ON				
★ Reserved								OFF				
★ Inhibit Active High									ON			
★ Inhibit Active Low									OFF			
★ MDB Special Mode	(No Error Code)(MDB Only)									ON		
★ MDB Normal Mode										OFF		
★ Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.
(2) Calibration card is needed.

XBA mini-PHP6(Pulse/MDB/ICT104V/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ 1 pulse / PHP 10			OFF	OFF
5 pulses / PHP 10			OFF	ON
10 pulses / PHP 10			ON	OFF
20 pulses / PHP 10			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(Other)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ Other Mode		OFF		
MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Connect with coin changer	ON			
Connect with ICT JPSTD Converter board	OFF			
Pulse Mode		ON		
★ Other Mode		OFF		
MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	PHP 20	PHP 20	PHP 20	PHP 20
BV2	PHP 50	PHP 50	PHP 50	PHP 50
BV3	PHP 100	PHP 100	PHP 100	PHP 100
BV4	PHP 500	PHP 500	PHP 200	PHP 200
BV5	PHP 1000	PHP 1000	PHP 500	PHP 500
BV6	PHP 200	PHP 200	PHP 1000	PHP 1000