

XBA mini-MYR6

XBA mini Option Switch Settings: 1(Pulse/MDB/ICT104V/ICT104U)

Supported bill M\$ 1, 5, 10, 20, 50, 100 6bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject M\$ 1	ON											
	Accept M\$ 1	OFF											
★	Reject M\$ 5		ON										
	Accept M\$ 5		OFF										
★	Reject M\$ 10			ON									
	Accept M\$ 10			OFF									
★	Reject M\$ 20				ON								
	Accept M\$ 20				OFF								
★	Reject M\$ 50 & 100					ON							
	Accept M\$ 50 & 100					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Stack Banknote when Power-up							ON					
	Reject Banknote when Power-up							OFF					
★	Enable Error Downtime								ON				
	Disable Error Downtime								OFF				
★	Inhibit Active High									ON			
	Inhibit Active Low									OFF			
★	Reserved										ON		
	Reserved										OFF		
★	Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
		60ms LO / 300ms HI										ON	OFF
		30ms LO / 50ms HI										OFF	ON
		150ms LO / 150ms HI										ON	ON

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses, you should reset the bill acceptor again.

(2) Calibration card is needed.

XBA mini-MYR6(Pulse/MDB/ICT104V/ICT104U)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / M\$ 1			OFF	OFF
	5 pulses / M\$ 1			OFF	ON
	10 pulses / M\$ 1			ON	OFF
	25 pulses / M\$ 1			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Connect with coin changer	ON			
	Connect with ICT JPSTD Converter board	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
★	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	M\$ 1	M\$ 1	M\$ 1	M\$ 1
BV2				
BV3	M\$ 5	M\$ 5	M\$ 5	M\$ 5
BV4	M\$ 10	M\$ 10	M\$ 10	M\$ 10
BV5	M\$ 50	M\$ 50	M\$ 50	M\$ 50
BV6	M\$ 100	M\$ 100	M\$ 100	M\$ 100
BV7	M\$ 20	M\$ 20	M\$ 20	M\$ 20

Interface Settings: 2(Other)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting