

XBA mini-UMR12(USD6+MYR6)

XBA mini Option Switch Settings: 1(Pulse/ICT104U)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.
Supported bill MYR 1, 5, 10, 20, 50, 100 6bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject USD 1 & 5 & 10	ON											
★	Accept USD 1 & 5 & 10	OFF											
★	Reject USD 20 & 50		ON										
★	Accept USD 20 & 50		OFF										
★	Reject USD 100			ON									
★	Accept USD 100			OFF									
★	Reject MYR 1 & 5 & 10				ON								
★	Accept MYR 1 & 5 & 10				OFF								
★	Reject MYR 20 & 50 & 100					ON							
★	Accept MYR 20 & 50 & 100					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Stack Banknote when Power-up							ON					
★	Reject Banknote when Power-up							OFF					
★	Reserved								ON				
★	Reserved								OFF				
★	Inhibit Active High									ON			
★	Inhibit Active Low									OFF			
★	Reserved										ON		
★	Reserved										OFF		
★	Interface Timing Conversion	50ms LO / 50ms HI						OFF	OFF				
		60ms LO / 300ms HI						ON	OFF				
		30ms LO / 50ms HI						OFF	ON				
		150ms LO / 150ms HI						ON	ON				

★ Manufacture setting

Note : 1. After setting dip switch of the credit pulses,you should reset the bill acceptor again.

2. Calibration card is needed.
3. Pulse Mode: USD 1=MYR 5

XBA mini-UMR12(Pulse/ICT104U)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
★	ICT104U Mode		OFF		
	1 pulse / MYR 1			OFF	OFF
	2 pulses / MYR 1			OFF	ON
	5 pulses / MYR 1			ON	OFF
	10 pulses / MYR 1			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	Interface Bill value	Pulse	ICT104U
BV1	MYR 1	MYR 1	BV7	USD 1	USD 1
BV2	MYR 5	MYR 5	BV8	USD 5	USD 5
BV3	MYR 10	MYR 10	BV9	USD 10	USD 10
BV4	MYR 20	MYR 20	BV10	USD 20	USD 20
BV5	MYR 50	MYR 50	BV11	USD 50	USD 50
BV6	MYR 100	MYR 100	BV12	USD 100	USD 100

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	ICT104U Mode		OFF		
★	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting