

## XBA mini-AOA4

### XBA mini Option Switch Settings: 1(Pulse/MDB/ICT104V/ICT104U)

Supported bill AOA 200, 500, 1000, 2000 4bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject AOA 200	ON											
★ Accept AOA 200	OFF											
★ Reject AOA 500		ON										
★ Accept AOA 500		OFF										
★ Reject AOA 1000			ON									
★ Accept AOA 1000			OFF									
★ Reject AOA 2000				ON								
★ Accept AOA 2000				OFF								
Reserved					ON							
★ Reserved					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec					ON							
★ Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF							
★ Stack Banknote when Power-up						ON						
★ Reject Banknote when Power-up						OFF						
★ Reserved							ON					
★ Reserved							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ Reserved									ON			
★ Reserved										OFF		
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

After setting dip switch of the credit pulses,you should reset the bill acceptor again.

Note : 1. Calibration card is needed.

## XBA mini-AOA4(Pulse/MDB/ICT104V/ICT104U)

### Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / AOA 100			OFF	OFF
	2 pulses / AOA 100			OFF	ON
	5 pulses / AOA 100			ON	OFF
	20 pulses / AOA 100			ON	ON

★ Manufacture setting

### Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Connect with coin changer	ON			
	Connect with ICT JPSTD Converter board	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
★	ICT104V Mode			ON	ON

★ Manufacture setting

### Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

### Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	AOA 200	AOA 200	AOA 200	AOA 200
BV2	AOA 500	AOA 500	AOA 500	AOA 500
BV3	AOA 1000	AOA 1000	AOA 1000	AOA 1000
BV4	AOA 2000	AOA 2000	AOA 2000	AOA 2000

### Interface Settings: 2(Other)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting