

L70/L70F-FJD6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill FJD 5, 7, 10, 20, 50, 100 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / FJD 1	OFF	OFF	OFF							
	2 Pulses / FJD 1	OFF	OFF	ON							
	3 Pulses / FJD 1	OFF	ON	OFF							
	4 Pulses / FJD 1	OFF	ON	ON							
	5 Pulses / FJD 1	ON	OFF	OFF							
	10 Pulses / FJD 1	ON	OFF	ON							
	20 Pulses / FJD 1	ON	ON	OFF							
	100 Pulses / FJD 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept FJD 5 & 7				ON						
	Reject FJD 5 & 7				OFF						
★	Accept FJD 10				ON						
	Reject FJD 10				OFF						
★	Accept FJD 20				ON						
	Reject FJD 20				OFF						
★	Accept FJD 50				ON						
	Reject FJD 50				OFF						
★	Accept FJD 100				ON						
	Reject FJD 100				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70/L70F-FJD6(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	FJD 5	FJD 5	FJD 5	FJD 5
BV2	FJD 7	FJD 7	FJD 7	FJD 7
BV3	FJD 10	FJD 10	FJD 10	FJD 10
BV4	FJD 20	FJD 20	FJD 20	FJD 20
BV5	FJD 50	FJD 50	FJD 50	FJD 50
BV6	FJD 100	FJD 100	FJD 100	FJD 100

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Mode		OFF	OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting