

# P70-HUF6

## P70/P5 DIP SWITCHES SETTING : 1(Pulse/ccTalk)

Supported bill Ft 500, 1000, 2000, 5000, 10000, 20000 6 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★ 1 Pulse / Ft 500	OFF	OFF	OFF								
2 Pulse / Ft 500	OFF	OFF	ON								
3 Pulse / Ft 500	OFF	ON	OFF								
4 Pulse / Ft 500	OFF	ON	ON								
5 Pulse / Ft 500	ON	OFF	OFF								
10 Pulse / Ft 500	ON	OFF	ON								
20 Pulse / Ft 500	ON	ON	OFF								
100 Pulse / Ft 500	ON	ON	ON								
★ Fast output Pulse <small>Lo= 75ms Hi= 75ms</small>											ON
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>											OFF
★ Inhibit level Active Low				ON							
★ Inhibit level Active High				OFF							
★ Accept Ft 500					ON						
★ Reject Ft 500					OFF						
★ Accept Ft 1000					ON						
★ Reject Ft 1000					OFF						
★ Accept Ft 2000					ON						
★ Reject Ft 2000					OFF						
★ Accept Ft 5000					ON						
★ Reject Ft 5000					OFF						
★ Accept Ft 10000 & 20000					ON						
★ Reject Ft 10000 & 20000					OFF						

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

# P70-HUF6/P5(Pulse/ccTalk)

## DIP SWITCHES SETTING : 2(Pulse)

## Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
★ Credit-Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
★ ccTalk Protocol		OFF		
★ Harness Disable			ON	
★ Harness Enable			OFF	
★ Reserved				ON
★ Reserved				OFF

Interface Bill value	Pulse	ccTalk
BV1	Ft 500	Ft 500
BV2	Ft 1000	Ft 1000
BV3	Ft 2000	Ft 2000
BV4	Ft 5000	Ft 5000
BV5	Ft 10000	Ft 10000
BV6	Ft 20000	Ft 20000

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

## DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ Encryption Mode	ON			
★ Decrypt Mode	OFF			
★ Pulse Protocol		ON		
★ ccTalk Protocol		OFF		
★ ccTalk Parameters Reset			ON	
★ Keep ccTalk Parameters			OFF	
★ Reserved				ON
★ Reserved				OFF

(★) Manufacture setting

Note:(1) ccTalk Parameters Reset

Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

\*This has to be done after finished calibration process.