

TAO-A.V-AUD5

TAO-A.V Option Switch Settings: 1(Pulse/MDB/ccNet)

Supported bill \$A 5, 10, 20, 50, 100 5bills.

TAO-V dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject \$A 5	ON											
★ Accept \$A 5	OFF											
★ Reject \$A 10		ON										
★ Accept \$A 10		OFF										
★ Reject \$A 20			ON									
★ Accept \$A 20			OFF									
★ Reject \$A 50				ON								
★ Accept \$A 50				OFF								
★ Reject \$A 100					ON							
★ Accept \$A 100					OFF							
★ Reserved					ON							
★ Reserved					OFF							
★ Pulse Moded	Other Moded											
★ Harness Disable	BA stops working when fishing				ON							
★ Harness Enable	Normal				OFF							
★ Inhibit Active High					ON							
★ Inhibit Active Low					OFF							
★ 1 pulse / \$A 5					OFF	OFF						
★ 5 pulses / \$A 5					ON	OFF						
★ 10 pulses / \$A 5					OFF	ON						
★ 20 pulses / \$A 5					ON	ON						
★ Interface Timing Conversion	50ms LO / 50ms HI						OFF	OFF				
	60ms LO / 300ms HI						ON	OFF				
	30ms LO / 50ms HI						OFF	ON				
	150ms LO / 150ms HI						ON	ON				

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

BV1=\$A 5, BV2=\$A 10, BV3=\$A 20, BV4=\$A 50, BV5=\$A 100

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

(4) CCNET DIP4 ON: BV3=\$A 5, BV4=\$A 10, BV5=\$A 20, BV6=\$A 50, BV7=\$A 100

OFF: BV1=\$A 5, BV2=\$A 10, BV3=\$A 20, BV4=\$A 50, BV5=\$A 100

TAO-A.V-AUD5(Pulse/MDB/ccNet)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
Australian channel value mapping	(Note,4)			ON
★ ICT channel value mapping				OFF

★ Manufacture setting

TAO-V-AUD5

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ccNet Mode		OFF	ON	
★ MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ccNet		Pulse	MDB
	DIP 4 ON	DIP 4 OFF		
BV1		\$A 5	\$A 5	\$A 5
BV2		\$A 10	\$A 10	\$A 10
BV3	\$A 5	\$A 20	\$A 20	\$A 20
BV4	\$A 10	\$A 50	\$A 50	\$A 50
BV5	\$A 20	\$A 100	\$A 100	\$A 100
BV6	\$A 50			
BV7	\$A 100			

Note : (4) CCNET DIP4 ON: BV3=\$A 5, BV4=\$A 10, BV5=\$A 20, BV6=\$A 50, BV7=\$A 100

OFF: BV1=\$A 5, BV2=\$A 10, BV3=\$A 20, BV4=\$A 50, BV5=\$A 100