

# V77E-JPY4

## V77E Option Switch Settings: 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill JPY 1000, 2000, 5000, 10000 4bills.

V77E dip-switch settings and functions:

|   | FUNCTION                  | SW1                           | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |  |
|---|---------------------------|-------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|--|
| ★ | Reject JPY 1000           | ON                            |     |     |     |     |     |     |     |     |     |     |     |  |
|   | Accept JPY 1000           | OFF                           |     |     |     |     |     |     |     |     |     |     |     |  |
| ★ | Reject JPY 2000           |                               | ON  |     |     |     |     |     |     |     |     |     |     |  |
| ★ | Accept JPY 2000           |                               | OFF |     |     |     |     |     |     |     |     |     |     |  |
| ★ | Reject JPY 5000           |                               |     | ON  |     |     |     |     |     |     |     |     |     |  |
| ★ | Accept JPY 5000           |                               |     | OFF |     |     |     |     |     |     |     |     |     |  |
| ★ | Reject JPY 10000          |                               |     |     | ON  |     |     |     |     |     |     |     |     |  |
| ★ | Accept JPY 10000          |                               |     |     | OFF |     |     |     |     |     |     |     |     |  |
| ★ | Accept only new JPY(2024) |                               |     |     |     | ON  |     |     |     |     |     |     |     |  |
| ★ | Accept all JPY            |                               |     |     |     | OFF |     |     |     |     |     |     |     |  |
| ★ | Reserved                  |                               |     |     |     |     | ON  |     |     |     |     |     |     |  |
| ★ | Reserved                  |                               |     |     |     |     | OFF |     |     |     |     |     |     |  |
|   | <b>Pulse Mode</b>         | <b>Other Mode</b>             |     |     |     |     |     |     |     |     |     |     |     |  |
| ★ | Harness Disable           | BA stops working when fishing |     |     |     |     |     | ON  |     |     |     |     |     |  |
| ★ | Harness Enable            | Normal                        |     |     |     |     |     | OFF |     |     |     |     |     |  |
| ★ | Inhibit Active High       |                               |     |     |     |     |     | ON  |     |     |     |     |     |  |
| ★ | Inhibit Active Low        |                               |     |     |     |     |     |     | OFF |     |     |     |     |  |
| ★ | 1 pulse / JPY 1000        |                               |     |     |     |     |     | OFF | OFF |     |     |     |     |  |
|   | 2 pulses / JPY 1000       |                               |     |     |     |     |     | ON  | OFF |     |     |     |     |  |
|   | 5 pulses / JPY 1000       |                               |     |     |     |     |     | OFF | ON  |     |     |     |     |  |
|   | 20 pulses / JPY 1000      |                               |     |     |     |     |     | ON  | ON  |     |     |     |     |  |
| ★ | Pulse Speed               | 50ms LO / 50ms HI             |     |     |     |     |     |     |     |     | OFF | OFF |     |  |
|   |                           | 60ms LO / 300ms HI            |     |     |     |     |     |     |     |     | ON  | OFF |     |  |
|   |                           | 30ms LO / 50ms HI             |     |     |     |     |     |     |     |     | OFF | ON  |     |  |
|   |                           | 150ms LO / 150ms HI           |     |     |     |     |     |     |     |     | ON  | ON  |     |  |

★ Manufacture setting

- Note : (1) Default setting  
 (2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.  
 (3) Remove the front cover and the dip-switch in on the CPU board.  
 (Please refer to "SW1" setting.)

# V77E-JPY4(Pulse/ICT104U/MDB/ICT104V)

## DIP SWITCHES SETTING : 3(Pulse)

|   | FUNCTION                 | SW1 | SW2 | SW3 | SW4 |
|---|--------------------------|-----|-----|-----|-----|
| ★ | Credit-Pulse Normal High | ON  |     |     |     |
|   | Credit-Pulse Normal Low  | OFF |     |     |     |
| ★ | Pulse Mode               |     | ON  | OFF |     |
|   | ICT104U Mode             |     | OFF | OFF |     |
|   | ICT104V Mode             |     | OFF | ON  |     |
|   | MDB Mode                 |     | ON  | ON  |     |
| ★ | Reserved                 |     |     |     | ON  |
|   |                          |     |     |     | OFF |

★ Manufacture setting

## DIP SWITCHES SETTING : 3(ICT104U)

|   | FUNCTION     | SW1 | SW2 | SW3 | SW4 |
|---|--------------|-----|-----|-----|-----|
| ★ | Reserved     | ON  |     |     |     |
|   |              | OFF |     |     |     |
| ★ | Pulse Mode   |     | ON  | OFF |     |
| ★ | ICT104U Mode |     | OFF | OFF |     |
|   | ICT104V Mode |     | OFF | ON  |     |
|   | MDB Mode     |     | ON  | ON  |     |
| ★ | Reserved     |     |     |     | ON  |
|   |              |     |     |     | OFF |

★ Manufacture setting

## DIP SWITCHES SETTING : 3(MDB)

|   | FUNCTION     | SW1 | SW2 | SW3 | SW4 |
|---|--------------|-----|-----|-----|-----|
| ★ | Reserved     | ON  |     |     |     |
|   | Reserved     | OFF |     |     |     |
| ★ | Pulse Mode   |     | ON  | OFF |     |
|   | ICT104U Mode |     | OFF | OFF |     |
|   | ICT104V Mode |     | OFF | ON  |     |
| ★ | MDB Mode     |     | ON  | ON  |     |
| ★ | Reserved     |     |     |     | ON  |
|   |              |     |     |     | OFF |

★ Manufacture setting

## Currency Assign Data

| Interface<br>Bill value | ICT104U   | Pulse     | MDB       | ICT104V   |
|-------------------------|-----------|-----------|-----------|-----------|
| BV1                     | JPY 1000  | JPY 1000  | JPY 1000  | JPY 1000  |
| BV2                     | JPY 2000  | JPY 2000  | JPY 2000  | JPY 2000  |
| BV3                     | JPY 5000  | JPY 5000  | JPY 5000  | JPY 5000  |
| BV4                     | JPY 10000 | JPY 10000 | JPY 10000 | JPY 10000 |

## DIP SWITCHES SETTING : 3(ICT104V)

|   | FUNCTION     | SW1 | SW2 | SW3 | SW4 |
|---|--------------|-----|-----|-----|-----|
| ★ | Reserved     | ON  |     |     |     |
|   |              | OFF |     |     |     |
| ★ | Pulse Mode   |     | ON  | OFF |     |
| ★ | ICT104U Mode |     | OFF | OFF |     |
| ★ | ICT104V Mode |     | OFF | ON  |     |
|   | MDB Mode     |     | ON  | ON  |     |
| ★ | Reserved     |     |     |     | ON  |
|   |              |     |     |     | OFF |

★ Manufacture setting