

**V7E/LX7-DOP6**

**V7E/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)**

**Supported bill DOP 20, 50, 100, 200, 500, 1000 6bill**

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject DOP 20 & 50	ON											
★ Accept DOP 20 & 50	OFF											
★ Reject DOP 100		ON										
★ Accept DOP 100		OFF										
★ Reject DOP 200			ON									
★ Accept DOP 200			OFF									
★ Reject DOP 500				ON								
★ Accept DOP 500				OFF								
★ Reject DOP 1000					ON							
★ Accept DOP 1000					OFF							
★ Rreserved						ON						
★ Rreserved						OFF						
<b>Pulse Mode</b>	<b>Other Mode</b>											
★ Harness Disable	BA stopped working when fishing						ON					
★ Harness Enable	Normal						OFF					
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / DOP 10								OFF	OFF			
★ 2 pulses / DOP 10								ON	OFF			
★ 5 pulses / DOP 10								OFF	ON			
★ 10 pulses / DOP 10								ON	ON			
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

**V7E/LX7-DOP6(Pulse/ICT104V/ICT104U/MDB)**

**DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data**

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
MDB Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	DOP 20	DOP 20	DOP 20	DOP 20
BV2	DOP 50	DOP 50	DOP 50	DOP 50
BV3	DOP 100	DOP 100	DOP 100	DOP 100
BV4	DOP 200	DOP 200	DOP 200	DOP 200
BV5	DOP 500	DOP 500	DOP 500	DOP 500
BV6	DOP 1000	DOP 1000	DOP 1000	DOP 1000

**DIP SWITCHES SETTING : 2(ICT104U)**

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
MDB Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

**DIP SWITCHES SETTING : 2(ICT104V)**

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
★ ICT104V Interface		ON	ON	
MDB Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

**DIP SWITCHES SETTING : 2(MDB)**

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
★ MDB Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting