

V7E+/LX7-TRY6

V7E+/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/ MDB)

Supported bill TRY 5, 10, 20, 50, 100, 200 6bills.

V7E+/LX7 dip-switch settings and functions:

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|-------------------------------|-------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject TRY 5 | ON | | | | | | | | | | | |
| ★ Accept TRY 5 | OFF | | | | | | | | | | | |
| ★ Reject TRY 10 | | ON | | | | | | | | | | |
| ★ Accept TRY 10 | | OFF | | | | | | | | | | |
| ★ Reject TRY 20 | | | ON | | | | | | | | | |
| ★ Accept TRY 20 | | | OFF | | | | | | | | | |
| ★ Reject TRY 50 | | | | ON | | | | | | | | |
| ★ Accept TRY 50 | | | | OFF | | | | | | | | |
| ★ Reject TRY 100 & 200 | | | | | ON | | | | | | | |
| ★ Accept TRY 100 & 200 | | | | | OFF | | | | | | | |
| ★ Reserved | | | | | | ON | | | | | | |
| ★ Reserved | | | | | | OFF | | | | | | |
| Pulse Mode | Other Mode | | | | | | | | | | | |
| ★ Harness Disable | BA stops working when fishing | | | | | | ON | | | | | |
| ★ Harness Enable | Normal | | | | | | OFF | | | | | |
| ★ Inhibit Active High | | | | | | | ON | | | | | |
| ★ Inhibit Active Low | | | | | | | OFF | | | | | |
| ★ 1 pulse / TRY 5 | | | | | | | | OFF | OFF | | | |
| ★ 5 pulses / TRY 5 | | | | | | | | ON | OFF | | | |
| ★ 10 pulses / TRY 5 | | | | | | | | OFF | ON | | | |
| ★ 20 pulses / TRY 5 | | | | | | | | ON | ON | | | |
| ★ Interface Timing Conversion | 50ms LO / 50ms HI | | | | | | | | OFF | OFF | | |
| | 60ms LO / 300ms HI | | | | | | | | ON | OFF | | |
| | 30ms LO / 50ms HI | | | | | | | | OFF | ON | | |
| | 150ms LO / 150ms HI | | | | | | | | ON | ON | | |

★ Manufacture setting

Note.1: Default setting.

Note.2: Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

Appendix

V7E+/LX7-TRY6(Pulse/ICT104V/ICT104U/ MDB)

Interface Settings: 2(Pulse)

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|----------------------------|-----|-----|-----|-----|
| ★ Credit-Pulse Normal HIGH | ON | | | |
| Credit-Pulse Normal LOW | OFF | | | |
| ★ Pulse Mode | | ON | OFF | |
| ICT104V Interface | | OFF | ON | |
| ICT104U Interface | | OFF | OFF | |
| MDB Interface | | ON | ON | |
| ★ Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

Interface Settings: 2(ICT104V)

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|---------------------|-----|-----|-----|-----|
| ★ Reserved | ON | | | |
| Reserved | OFF | | | |
| Pulse Mode | | ON | OFF | |
| ★ ICT104V Interface | | OFF | ON | |
| ICT104U Interface | | OFF | OFF | |
| MDB Interface | | ON | ON | |
| ★ Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

Interface Settings: 2(MDB)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|-----|-----|-----|-----|
| ★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 | ON | | | |
| | OFF | | | |
| Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0 | | | | |
| Pulse Mode | | ON | OFF | |
| ICT104V Interface | | OFF | ON | |
| ICT104U Interface | | OFF | OFF | |
| ★ MDB Interface | | ON | ON | |
| ★ Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

Currency Assign Data

| Interface Bill value | MDB | Pulse | ICT104U | ICT104V |
|-------------------------|---------|---------|---------|---------|
| BV1 | TRY 5 | TRY 5 | TRY 5 | TRY 5 |
| BV2 | TRY 10 | TRY 10 | TRY 10 | TRY 10 |
| BV3 | TRY 20 | TRY 20 | TRY 20 | TRY 20 |
| BV4 | TRY 50 | TRY 50 | TRY 50 | TRY 50 |
| BV5 | TRY 100 | TRY 100 | TRY 100 | TRY 100 |
| BV6 | TRY 200 | TRY 200 | TRY 200 | TRY 200 |

Interface Settings: 2(ICT104U)

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|---------------------|-----|-----|-----|-----|
| ★ Reserved | ON | | | |
| Reserved | OFF | | | |
| Pulse Mode | | ON | OFF | |
| ★ ICT104V Interface | | OFF | ON | |
| ICT104U Interface | | OFF | OFF | |
| ★ MDB Interface | | ON | ON | |
| ★ Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting