

A6E-USD4

A6E Option Switch Settings: 1 (Pulse/5V ENABLE/ICT002U)

Supported bill US\$ 1, 5, 10, 20 4bills.

A6E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject US\$ 1	ON											
★	Accept US\$ 1	OFF											
	Reject US\$ 5		ON										
★	Accept US\$ 5		OFF										
	Reject US\$ 10			ON									
★	Accept US\$ 10			OFF									
	Reject US\$ 20				ON								
★	Accept US\$ 20				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Interface(VCP) Mode	(Note.3)				ON							
★	Diagnostic Mode	(Note.4)				OFF							
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low	(Note.5)							OFF				
★	1 pulse / US\$ 1								OFF	OFF			
	2 pulse / US\$ 1								ON	OFF			
	4 pulse / US\$ 1								OFF	ON			
	20 pulse / US\$ 1								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Default setting(Factory configuration has all switches in the OFF position.)

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Interface(VCP) Mode is for USB connection of ICT002U.

(4) Diagnostic Mode is for USB connection of Autotest tool.

(5) SW8 of the 8-switch DIP is for pulse 5V Enable only.

A6E-USD4(Pulse/5V Enable/ICT002U)

Remove the front cover and the dip-switch is on the CPU board.

A6E Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ICT002U Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
★	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

A6E Interface Settings: 4 (ICT002U)

	INTERFACE	SW1	SW2	SW3	SW4
	Reserved	ON			
★		OFF			
	Pulse Mode		ON		
★	ICT002U Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
★	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	US\$ 1	US\$ 1
BV2	US\$ 5	US\$ 5
BV3	US\$ 10	US\$ 10
BV4	US\$ 20	US\$ 20