

BR2300-GBP4

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill

English banknotes: Bank of England £ 5, £ 10, £ 20, £ 50

Scottish banknotes: Bank of Scotland £ 5, £ 10, £ 20

Royal Bank & Clydesdale Bank £ 5, £ 10

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject All £ 5 bills	ON									
	Accept All £ 5 bills	OFF									
★	Reject All £ 10 bills		ON								
	Accept All £ 10 bills		OFF								
★	Reject All £ 20 bills			ON							
	Accept All £ 20 bills			OFF							
★	Reject All £ 50 bills				ON						
	Accept All £ 50 bills				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	(MDB Only)				ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON	
	Decrypt MODE	Standard MDB Recycler Function				★ Connect with RS232 Connector				OFF	

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: Calibration card is needed.

BR2300-GBP4 (MDB+ICT-BC+ccTalk)

Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB	Recycler banknote inventory	
BV1	£ 5	£ 5	£ 5	£ 5	45 pcs
BV2	£ 10	£ 10	£ 10	£ 10	45 pcs
BV3	£ 20	£ 20	£ 20	£ 20	40 pcs
BV4	£ 50	£ 50	£ 50	£ 50	40 pcs