

# BR2300-KRW4

## BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill KRW 1000, 5000, 10000, 50000 4 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
	Reject KRW 1000 & 5000	ON									
★	Accept KRW 1000 & 5000	OFF									
	Reject KRW 10000		ON								
★	Accept KRW 10000		OFF								
	Reject KRW 50000			ON							
★	Accept KRW 50000			OFF							
	High Acceptance (Note.3)				ON						
★	High Security				OFF						
★	Scaling Factor (SF)=100 Decimal Point Position(DPP)=2	(MDB only)				ON					
	Scaling Factor (SF)=1 Decimal Point Position(DPP)=0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON	
	Decrypt MODE	Standard MDB Recycler Function				★ Connect with RS232 Connector				OFF	

### ★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.4: Calibrate card is needed.

## Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB
BV1	KRW 1000	KRW 1000	KRW 1000
BV2	KRW 5000	KRW 5000	KRW 5000
BV3	KRW 10000	KRW 10000	KRW 10000
BV4	KRW 50000	KRW 50000	KRW 50000

Recycler banknote inventory	
KRW 1000	45 pcs
KRW 5000	45 pcs
KRW 10000	40 pcs
KRW 50000	40 pcs