

BR2300-PHP6

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill PHP 20, 50, 100, 200, 500, 1000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject PHP 20 & 50	ON									
	Accept PHP 20 & 50	OFF									
★	Reject PHP 100 & 200		ON								
	Accept PHP 100 & 200		OFF								
★	Reject PHP 500 & 1000			ON							
	Accept PHP 500 & 1000			OFF							
★	High Acceptance (Note.3)			ON							
	High Security			OFF							
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 (MDB Only)				ON						
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				OFF						
★	Normal					OFF	OFF				
	Load Banknote to Recycle					ON	OFF				
	Load Banknote to Stacker					OFF	ON				
	Unload Banknote to Stacker					ON	ON				
★	ccTalk							ON	OFF		
	ccTalk (Note.1)							OFF	ON		
★	MDB Mode							OFF	OFF		
★	ICT-BC Mode							ON	ON		
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON	
	Decrypt MODE	Standard MDB Recycler Function				★ Connect with RS232 Connector				OFF	

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1. Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

2. Recycled Banknote represents as a virtual MDB coin type.

3. High acceptance mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor.

4. Calibration card is needed.

BR2300-PHP6 (MDB/ICT-BC/ccTalk)

Currency Assign Data

Interface Bill value	MDB		ICT-BC		ccTalk		Recycler banknote inventory		
BV1	PHP	20	PHP	20	PHP	20	PHP	20	40 pcs
BV2	PHP	50	PHP	50	PHP	50	PHP	50	40 pcs
BV3	PHP	100	PHP	100	PHP	100	PHP	100	40 pcs
BV4	PHP	200	PHP	200	PHP	200	PHP	200	40 pcs
BV5	PHP	500	PHP	500	PHP	500	PHP	500	40 pcs
BV6	PHP	1000	PHP	1000	PHP	1000	PHP	1000	40 pcs