

BR2300-RUB6

BR2300 DIP SWITCHES SETTING : (MDB/ICT104R/ccTalk)

Supported bill RUB 10, 50, 100, 500, 1000, 5000 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject RUB 10 (Note.3)	ON									
	Accept RUB 10 (Note.3)	OFF									
★	Reject RUB 50 & 100		ON								
	Accept RUB 50 & 100		OFF								
★	Reject RUB 500 & 1000			ON							
	Accept RUB 500 & 1000			OFF							
★	Reject RUB 5000				ON						
	Accept RUB 5000				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	(MDB only)				ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT104R Mode								ON	ON	
	ccTalk	MDB Mode				ICT104R Mode					
★	Encryption MODE	Virtual MDB Recycler Function (Note.2)				Rseerved					ON
	Decrypt MODE	Standard MDB Recycler Function				Rseerved					OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycked Banknote represents virtual MDB coin type.

Note.3:** MDB Mode:

When Dip 1 is OFF,Reject RUB 5000.

When Dip 1 is ON,Accept RUB 5000.

Note.4: calibrate card.

Currency Assign Data

Interface Bill value	ccTalk	ICT104R	MDB	
			When Dip 1 is OFF	When Dip 1 is ON
BV1	RUB 10	RUB 10	RUB 10	RUB 50
BV2	RUB 50	RUB 50	RUB 50	RUB 100
BV3	RUB 100	RUB 100	RUB 100	RUB 500
BV4	RUB 500	RUB 500	RUB 500	RUB 1000
BV5	RUB 1000	RUB 1000	RUB 1000	RUB 5000
BV6	RUB 5000	RUB 5000		