

BRV-BYN4

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill BYN 5, 10, 20, 50 4bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject BYN 5	ON											
★ Accept BYN 5	OFF											
★ Reject BYN 10		ON										
★ Accept BYN 10		OFF										
★ Reject BYN 20			ON									
★ Accept BYN 20			OFF									
★ Reject BYN 50				ON								
★ Accept BYN 50				OFF								
★ Reserved				ON								
★ Reserved				OFF								
★ Normal					OFF	OFF						
Load Banknote to Recycle					ON	OFF						
Load Banknote to Stacker					OFF	ON						
Unload Banknote to Stacker					ON	ON						
★ Reserved								ON				
★ Reserved								OFF				
★ MDB Mode	SW1	SW2	SW3	SW4	JPSTD Dummy Mode							
★ Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★ Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
★ Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★ Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
★ Reserved					4 Bank Note Limitation Per Transaction	ON	ON	OFF				
★ Reserved					5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
★ Reserved					6 Bank Note Limitation Per Transaction	ON	OFF	ON				
★ Reserved					7 Bank Note Limitation Per Transaction	OFF	ON	ON				
★ Virtual MDB Recycler Function (Note.4)				ON	No Refund After the Deal						ON	
★ Standard MDB Recycler Function				OFF	★ Refund After the Deal						OFF	

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibration card is needed.

(4) Recycled Banknote represents virtual MDB coin type.

BRV-BYN4(ICT-BC/MDB/JPSTD Dummy)

Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
★ Reserved	ON			
★ Reserved	OFF			
★ Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
★ MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
★ Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

INTERFACE	SW5	SW6	SW7	SW8
★ Escrow (JPSTD Dummy Mode)	ON			
★ No Escrow (JPSTD Dummy Mode)	OFF			
★ Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
★ Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
★ Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
★ Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB	Recycler banknote inventory	
BV1	BYN 5	BYN 5	BYN 5	BYN 5	35 pcs
BV2	BYN 10	BYN 10	BYN 10	BYN 10	35 pcs
BV3	BYN 20	BYN 20	BYN 20	BYN 20	35 pcs
BV4	BYN 50	BYN 50	BYN 50	BYN 50	35 pcs