

## BRV-RON3

### BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill RON 1, 5, 10 3bills.

BRV dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject RON 1	ON											
★	Accept RON 1	OFF											
	Reject RON 5		ON										
★	Accept RON 5		OFF										
	Reject RON 10			ON									
★	Accept RON 10			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved				OFF								
★	Normal					OFF	OFF						
	Load Banknote to Recycle					ON	OFF						
	Load Banknote to Stacker					OFF	ON						
	Unload Banknote to cash out					ON	ON						
	Reserved								ON				
★	Reserved								OFF				
	<b>MDB Mode</b>	SW1	SW2	SW3	SW4	<b>JPSTD Dummy Mode</b>							
	Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★	Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
	Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★	Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
	Reserved					4 Bank Note Limitation Per Transaction	ON	ON	OFF				
	Reserved					5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
★	Reserved					6 Bank Note Limitation Per Transaction	ON	OFF	ON				
	Reserved					7 Bank Note Limitation Per Transaction	OFF	ON	ON				
	Virtual MDB Recycler Function (Note.4)				ON	No Refund After the Deal						ON	
★	Standard MDB Recycler Function				OFF	★ Refund After the Deal						OFF	

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibration card is needed.

(4) Recycked Banknote represents virtual MDB coin type.

## BRV-RON3(ICT-BC/MDB/JPSTD Dummy)

### Interface Settings: 2(ICT-BC)

	INTERFACE	SW5	SW6	SW7	SW8
	Reserved	ON			
★	Reserved	OFF			
	Connect with MDB Connector		ON		
★	Connect with RS232 Connector		OFF		
	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
	Reserved			ON	OFF
★	ICT-BC Mode			ON	ON

★ Manufacture setting

### Interface Settings: 2(JPSTD Dummy)

	INTERFACE	SW5	SW6	SW7	SW8
	Escrow (JPSTD Dummy Mode)	ON			
★	No Escrow (JPSTD Dummy Mode)	OFF			
	Reserved		ON		
★	Reserved		OFF		
	MDB Mode			OFF	OFF
★	JPSTD Dummy Mode			OFF	ON
	Reserved			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

### Interface Settings: 2(MDB)

	INTERFACE	SW5	SW6	SW7	SW8
★	Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
	Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
	Reserved		ON		
★	Reserved		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
	Reserved			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

## Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB	Recycler banknote inventory	
BV1	RON 1	RON 1	RON 1	RON 1	40 pcs
BV2	RON 5	RON 5	RON 5	RON 5	35 pcs
BV3	RON 10	RON 10	RON 10	RON 10	35 pcs