

BRV-SAR3

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill SAR 1, 5, 10 3bills.

BRV dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject SAR 1	ON											
★	Accept SAR 1	OFF											
★	Reject SAR 5		ON										
★	Accept SAR 5		OFF										
★	Reject SAR 10			ON									
★	Accept SAR 10			OFF									
★	Reserved				ON								
★	Reserved				OFF								
★	Reserved					ON							
★	Reserved					OFF							
★	Normal						OFF	OFF					
	Load Banknote to Recycle					ON		OFF					
	Load Banknote to Stacker					OFF		ON					
	Unload Banknote to Stacker					ON		ON					
	Reserved								ON				
★	Reserved								OFF				
	MDB Mode	SW1	SW2	SW3	SW4	JPSTD Dummy Mode							
★	Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
	Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
	Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★	Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
	Reserved					4 Bank Note Limitation Per Transaction	ON	ON	OFF				
	Reserved					5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
★	Reserved					6 Bank Note Limitation Per Transaction	ON	OFF	ON				
	Reserved					7 Bank Note Limitation Per Transaction	OFF	ON	ON				
	Virtual MDB Recycler Function (Note.4)				ON	No Refund After the Deal						ON	
★	Standard MDB Recycler Function				OFF	★ Refund After the Deal						OFF	

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibrate card.

(4) Recycled Banknote represents virtual MDB coin type.

(5) Medium Security mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

BRV-SAR3(ICT-BC/MDB/JPSTD Dummy)

Interface Settings: 2(ICT-BC)

	INTERFACE	SW5	SW6	SW7	SW8
★	Reserved	ON			
★	Reserved	OFF			
★	Connect with MDB Connector		ON		
★	Connect with RS232 Connector		OFF		
	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
	Reserved			ON	OFF
★	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

	INTERFACE	SW5	SW6	SW7	SW8
★	Escrow (JPSTD Dummy Mode)	ON			
★	No Escrow (JPSTD Dummy Mode)	OFF			
★	Reserved		ON		
★	Reserved		OFF		
	MDB Mode			OFF	OFF
★	JPSTD Dummy Mode			OFF	ON
	Reserved			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	INTERFACE	SW5	SW6	SW7	SW8
★	Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
	Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
	Reserved		ON		
★	Reserved		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
	Reserved			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB	Recycler banknote inventory	
BV1	SAR 1	SAR 1	SAR 1	SAR 1	35 pcs
BV2	SAR 5	SAR 5	SAR 5	SAR 5	35 pcs
BV3	SAR 10	SAR 10	SAR 10	SAR 10	30 pcs