

L70T-USD4

L70T DIP SWITCHES SETTING : 1(Pulse/RS232 A0/V2.2)

Supported bill USD 1, 5, 10, 20 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / USD 1	OFF	OFF	OFF							
	2 Pulses / USD 1	OFF	OFF	ON							
	3 Pulses / USD 1	OFF	ON	OFF							
	4 Pulses / USD 1	OFF	ON	ON							
	5 Pulses / USD 1	ON	OFF	OFF							
	10 Pulses / USD 1	ON	OFF	ON							
	20 Pulses / USD 1	ON	ON	OFF							
	100 Pulses / USD 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept USD 1				ON						
	Reject USD 1				OFF						
★	Accept USD 5				ON						
	Reject USD 5				OFF						
★	Accept USD 10				ON						
	Reject USD 10				OFF						
★	Accept USD 20				ON						
	Reject USD 20				OFF						
★	Reserved				ON						
	Reserved				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse mode.

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	V2.2
BV1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5	USD 5
BV3	USD 10	USD 10	USD 10
BV4	USD 20	USD 20	USD 20

L70T-USD4(Pulse/RS232 A0/V2.2)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	RS232 A0 Mode		ON	ON	
	V2.2 Mode		OFF	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	RS232 A0 Mode		ON	ON	
	V2.2 Mode		OFF	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

RS232 A0 INFORMATION	
BillType Data	
Code	Denomination
1	USD 1
2	Reserved
3	USD 5
4	USD 10
5	USD 20
6	Reserved
7	Reserved
8	Reserved
9	Reserved

★ Manufacture setting

DIP SWITCHES SETTING : 2(V2.2)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	RS232 A0 Mode		ON	ON	
★	V2.2 Mode		OFF	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting