

LAK8

L77&L77F DIP SWITCHES SETTING : 1(Pulse/ICT104/ccNet)

Supported bill LAK 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 8bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / LAK 500	OFF	OFF	OFF							
2 Pulse / LAK 500	OFF	OFF	ON							
3 Pulse / LAK 500	OFF	ON	OFF							
4 Pulse / LAK 500	OFF	ON	ON							
5 Pulse / LAK 500	ON	OFF	OFF							
10 Pulse / LAK 500	ON	OFF	ON							
20 Pulse / LAK 500	ON	ON	OFF							
100 Pulse / LAK 500	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept LAK 500 & 1000						ON				
Reject LAK 500 & 1000						OFF				
★ Accept LAK 2000 & 5000							ON			
Reject LAK 2000 & 5000							OFF			
★ Accept LAK 10000 & 20000								ON		
Reject LAK 10000 & 20000								OFF		
★ Accept LAK 50000									ON	
Reject LAK 50000									OFF	
★ Accept LAK 100000										ON
Reject LAK 100000										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse model.

Currency Assign Data

Interface Bill value	Pulse	ccNet	Interface Bill value	Pulse	ICT
BV1	500	500	BV5	10000	10000
BV2	1000	1000	BV6	20000	20000
BV3	2000	2000	BV7	50000	50000
BV4	5000	5000	BV8	100000	100000

L77&L77F-LAK8(Pulse/ICT104/ccNet)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ ICT Protocol Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ CcNet Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting