



TRY6

L77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ccTalk)

Supported bill Lira 5, 10, 20, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / 5 Lira	OFF	OFF	OFF							
	2 Pulses / 5 Lira	OFF	OFF	ON							
	3 Pulses / 5 Lira	OFF	ON	OFF							
	4 Pulses / 5 Lira	OFF	ON	ON							
	5 Pulses / 5 Lira	ON	OFF	OFF							
	10 Pulses / 5 Lira	ON	OFF	ON							
	20 Pulses / 5 Lira	ON	ON	OFF							
	100 Pulses / 5 Lira	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept 5 Lira & 10 Lira				ON						
	Reject 5 Lira & 10 Lira				OFF						
★	Accept 20 Lira				ON						
	Reject 20 Lira				OFF						
★	Accept 50 Lira				ON						
	Reject 50 Lira				OFF						
★	Accept 100 Lira				ON						
	Reject 100 Lira				OFF						
★	Accept 200 Lira				ON						
	Reject 200 Lira				OFF						

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4	
★	Pulse Normal High	ON				
	Pulse Normal Low	OFF				
★	Pulse Mode		ON			
	ccTalk Mode		OFF			
★	Reserved			ON		
				OFF		
★						ON
						OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	ccTalk Mode		OFF		
★	ccTalk Parameters Restore Switch Please see "Note" for detail			ON	
	ccTalk Interface			OFF	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.