

BAM4

L77&L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/RS232 A0)

Supported bill BAM 10, 20, 50, 100 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / BAM 10	OFF	OFF	OFF							
	2 Pulses / BAM 10	OFF	OFF	ON							
	3 Pulses / BAM 10	OFF	ON	OFF							
	4 Pulses / BAM 10	OFF	ON	ON							
	5 Pulses / BAM 10	ON	OFF	OFF							
	10 Pulses / BAM 10	ON	OFF	ON							
	20 Pulses / BAM 10	ON	ON	OFF							
	100 Pulses / BAM 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept BAM 10						ON				
	Reject BAM 10						OFF				
★	Accept BAM 20							ON			
	Reject BAM 20							OFF			
★	Accept BAM 50								ON		
	Reject BAM 50								OFF		
★	Accept BAM 100									ON	
	Reject BAM 100									OFF	
	Reserved										ON
★	Reserved										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L77&L77F-BAM4(Pulse/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	RS232 A0 Protocol Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	RS232 A0
BV1	BAM 10	BAM 10
BV2	BAM 20	BAM 20
BV3	BAM 50	BAM 50
BV4	BAM 100	BAM 100

DIP SWITCHES SETTING : 3(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	RS232 A0 Protocol Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	Reserved
4	BAM 10
5	BAM 20
6	BAM 50
7	BAM 100
8	Reserved
9	Reserved