

L77F/PL77-BYN5

L77F/PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/RS232 A0)

Supported bill Br 5, 10, 20, 50, 100 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Br 5	OFF	OFF	OFF							
2 Pulses / Br 5	OFF	OFF	ON							
3 Pulses / Br 5	OFF	ON	OFF							
4 Pulses / Br 5	OFF	ON	ON							
5 Pulses / Br 5	ON	OFF	OFF							
10 Pulses / Br 5	ON	OFF	ON							
20 Pulses / Br 5	ON	ON	OFF							
50 Pulses / Br 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Br 5						ON				
Reject Br 5						OFF				
★ Accept Br 10							ON			
Reject Br 10							OFF			
★ Accept Br 20								ON		
Reject Br 20								OFF		
★ Accept Br 50									ON	
Reject Br 50									OFF	
★ Accept Br 100										ON
Reject Br 100										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L77F/PL77-BYR5(Pulse/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
RS232 A0 Interface Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4	RS232 A0 INFORMATION
Reserved	ON				
Reserved	OFF				Code Denomination
★ Pulse Mode		ON			1 Reserved
★ RS232 A0 Interface Mode		OFF			2 Br 5
★ Reserved			ON		3 Br 10
			OFF		4 Br 20
				ON	5 Br 50
				OFF	6 Br 100

★ Manufacture setting

Currency Assign Data

Interface Bill value	RS232 A0	Pulse
BV1	Br 5	Br 5
BV2	Br 10	Br 10
BV3	Br 20	Br 20
BV4	Br 50	Br 50
BV5	Br 100	Br 100