

L77F/PL77-GEL6

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104/MDB)

Supported bill Lari 5, 10, 20, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Lari 5	OFF	OFF	OFF							
	2 Pulse / Lari 5	OFF	OFF	ON							
	3 Pulse / Lari 5	OFF	ON	OFF							
	4 Pulse / Lari 5	OFF	ON	ON							
	5 Pulse / Lari 5	ON	OFF	OFF							
	10 Pulse / Lari 5	ON	OFF	ON							
	20 Pulse / Lari 5	ON	ON	OFF							
	100 Pulse / Lari 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept Lari 5						ON				
	Reject Lari 5						OFF				
★	Accept Lari 10							ON			
	Reject Lari 10							OFF			
★	Accept Lari 20								ON		
	Reject Lari 20								OFF		
★	Accept Lari 50									ON	
	Reject Lari 50									OFF	
★	Accept Lari 100 & 200										ON
	Reject Lari 100 & 200										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L77F/PL77-GEL6 (Pulse/ICT104/MDB)

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104 Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	ICT	Pulse	MDB
BV3	Lari 5	Lari 5	Lari 5
BV4	Lari 10	Lari 10	Lari 10
BV5	Lari 20	Lari 20	Lari 20
BV6	Lari 50	Lari 50	Lari 50
BV7	Lari 100	Lari 100	Lari 100
BV8	Lari 200	Lari 200	Lari 200

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104 Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104 Interface		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting