

## L77F/PL77-KZT5

### L77F/PL77 Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill KZT 200, 500, 1000, 2000, 5000 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / KZT 100	OFF	OFF	OFF							
2 Pulses / KZT 100	OFF	OFF	ON							
3 Pulses / KZT 100	OFF	ON	OFF							
4 Pulses / KZT 100	OFF	ON	ON							
5 Pulses / KZT 100	ON	OFF	OFF							
10 Pulses / KZT 100	ON	OFF	ON							
20 Pulses / KZT 100	ON	ON	OFF							
100 Pulses / KZT 100	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept KZT 200 & 500						ON				
Reject KZT 200 & 500						OFF				
★ Accept KZT 1000							ON			
Reject KZT 1000							OFF			
★ Accept KZT 2000								ON		
Reject KZT 2000								OFF		
★ Accept KZT 5000									ON	
Reject KZT 5000									OFF	
Simulation BillBox Has Been Removed										ON
★ Default										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

### Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccNet	ICT104U
BV1	200	200	200	200
BV2	500	500	500	500
BV3	1000	1000	1000	1000

Interface Bill value	Pulse	RS232 A0	ccNet	ICT104U
BV4	2000	2000	2000	2000
BV5	5000	5000	5000	5000

## L77F/PL77-KZT5(Pulse/RS232 A0/ccNet/ICT104U)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
RS232 A0 Mode		ON	ON	
★ Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

#### RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	KZT 200
3	KZT 500
4	KZT 1000
5	KZT 2000
6	KZT 5000

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
Baud rate 19200	ON			
★ Baud rate 9600	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
★ ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting