

L77F/PL77-OMR5

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill OMR 0.1, 0.5, 1, 5, 10 5 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / OMR 0.1	OFF	OFF	OFF							
	2 Pulses / OMR 0.1	OFF	OFF	ON							
	3 Pulses / OMR 0.1	OFF	ON	OFF							
	4 Pulses / OMR 0.1	OFF	ON	ON							
	5 Pulses / OMR 0.1	ON	OFF	OFF							
	10 Pulses / OMR 0.1	ON	OFF	ON							
	20 Pulses / OMR 0.1	ON	ON	OFF							
	100 Pulses / OMR 0.1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept OMR 0.1						ON				
	Reject OMR 0.1						OFF				
★	Accept OMR 0.5							ON			
	Reject OMR 0.5							OFF			
★	Accept OMR 1								ON		
	Reject OMR 1								OFF		
★	Accept OMR 5									ON	
	Reject OMR 5									OFF	
★	Accept OMR 10										ON
	Reject OMR 10										OFF

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.

L77F/PL77-OMR5 (Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	OMR 0.1	OMR 0.1	OMR 0.1	OMR 0.1
BV2	OMR 0.5	OMR 0.5	OMR 0.5	OMR 0.5
BV3	OMR 1	OMR 1	OMR 1	OMR 1
BV4	OMR 5	OMR 5	OMR 5	OMR 5
BV5	OMR 10	OMR 10	OMR 10	OMR 10

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 1	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting