

L77F/PL77-PLN6

L77F&PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill PLN 10, 20, 50, 100, 200, 500 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / PLN 10	OFF	OFF	OFF							
	2 Pulse / PLN 10	OFF	OFF	ON							
	3 Pulse / PLN 10	OFF	ON	OFF							
	4 Pulse / PLN 10	OFF	ON	ON							
	5 Pulse / PLN 10	ON	OFF	OFF							
	10 Pulse / PLN 10	ON	OFF	ON							
	20 Pulse / PLN 10	ON	ON	OFF							
	100 Pulse / PLN 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept PLN 10 & 20				ON						
	Reject PLN 10 & 20				OFF						
★	Accept PLN 50				ON						
	Reject PLN 50				OFF						
★	Accept PLN 100				ON						
	Reject PLN 100				OFF						
★	Accept PLN 200				ON						
	Reject PLN 200				OFF						
★	Accept PLN 500				ON						
	Reject PLN 500				OFF						

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L77F/PL77-PLN6(Pulse/ICT104U/ccTalk)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Interface		ON	OFF	
	ICT104U Interface		ON	ON	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
★	ICT104U Interface		ON	ON	
	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	PLN 10	PLN 10	PLN 10
BV2	PLN 20	PLN 20	PLN 20
BV3	PLN 50	PLN 50	PLN 50
BV4	PLN 100	PLN 100	PLN 100
BV5	PLN 200	PLN 200	PLN 200
BV6	PLN 500	PLN 500	PLN 500

Interface Settings: 2(ccTalk)

	INTERFACE	SW1	SW2	SW3	SW4
★	8-bit checksum	ON			
	CRC 16-bit checksum	OFF			
	Pulse Interface		ON	OFF	
	ICT104U Interface		ON	ON	
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF