

L77F&PL77-THB5

L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104V/MDB)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / THB 10	OFF	OFF	OFF							
	2 Pulse / THB 10	OFF	OFF	ON							
	3 Pulse / THB 10	OFF	ON	OFF							
	4 Pulse / THB 10	OFF	ON	ON							
	5 Pulse / THB 10	ON	OFF	OFF							
	10 Pulse / THB 10	ON	OFF	ON							
	20 Pulse / THB 10	ON	ON	OFF							
	100 Pulse / THB 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept THB 20 & 50				ON						
	Reject THB 20 & 50				OFF						
★	Accept THB 100				ON						
	Reject THB 100				OFF						
★	Accept THB 500				ON						
	Reject THB 500				OFF						
★	Accept THB 1000				ON						
	Reject THB 1000				OFF						
★	High Security									ON	
	High Acceptance (Nota.3)									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

L77F&PL77-THB5P3/P6(Pulse/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104V Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
	Power On Motor Plus				ON
★	Power On Motor Minus				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104V	MDB
BV1	THB 20	THB 20	THB 20
BV2	THB 50	THB 50	THB 50
BV3	THB 100	THB 100	THB 100
BV4	THB 500	THB 500	THB 500
BV5	THB 1000	THB 1000	THB 1000

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104V Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
	Power On Motor Plus				ON
★	Power On Motor Minus				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104V Interface		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
	Power On Motor Plus				ON
★	Power On Motor Minus				OFF

★ Manufacture setting