

L77F&PL77-THB5

L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT10A/ICT104U)

Supported bill ₪ 20, 50, 100, 500, 1000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / ₪ 10	OFF	OFF	OFF							
	2 Pulse / ₪ 10	OFF	OFF	ON							
	3 Pulse / ₪ 10	OFF	ON	OFF							
	4 Pulse / ₪ 10	OFF	ON	ON							
	5 Pulse / ₪ 10	ON	OFF	OFF							
	10 Pulse / ₪ 10	ON	OFF	ON							
	20 Pulse / ₪ 10	ON	ON	OFF							
	100 Pulse / ₪ 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept ₪ 20 & 50				ON						
	Reject ₪ 20 & 50				OFF						
★	Accept ₪ 100				ON						
	Reject ₪ 100				OFF						
★	Accept ₪ 500				ON						
	Reject ₪ 500				OFF						
★	Accept ₪ 1000				ON						
	Reject ₪ 1000				OFF						
★	High Security				ON						
	High Acceptance (Note.3)				OFF						

★ Manufacture setting

Note:(1)Please reset the bill acceptor after any changes on Dip switch.

(2)Dip Switch 1 to 5 are only for Pulse mode.

(3)High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Currency Assign Data

Interface Bill value	ICT104U	Pulse	ICT10A
BV1	₪ 20	₪ 20	₪ 20
BV2	₪ 50	₪ 50	₪ 50
BV3	₪ 100	₪ 100	₪ 100
BV4	₪ 500	₪ 500	₪ 500
BV5	₪ 1000	₪ 1000	₪ 1000

L77F&PL77-THB5 (Pulse/ICT10A/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		ON	ON	
	ICT10A Mode		OFF	ON	
	Reserved		OFF	OFF	
	Power On Motor Plus				ON
★	Power On Motor Minus				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		ON	ON	
	ICT10A Mode		OFF	ON	
	Reserved		OFF	OFF	
	Power On Motor Plus				ON
★	Power On Motor Minus				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT10A)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		ON	ON	
★	ICT10A Mode		OFF	ON	
	Reserved		OFF	OFF	
	Power On Motor Plus				ON
★	Power On Motor Minus				OFF

★ Manufacture setting