

L77F/PL77-XOF4

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill XOF 500, 1000, 2000, 5000 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / XOF 500	OFF	OFF	OFF							
2 Pulse / XOF 500	OFF	OFF	ON							
3 Pulse / XOF 500	OFF	ON	OFF							
4 Pulse / XOF 500	OFF	ON	ON							
5 Pulse / XOF 500	ON	OFF	OFF							
10 Pulse / XOF 500	ON	OFF	ON							
20 Pulse / XOF 500	ON	ON	OFF							
100 Pulse / XOF 500	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept XOF 500						ON				
Reject XOF 500						OFF				
★ Accept XOF 1000							ON			
Reject XOF 1000							OFF			
★ Accept XOF 2000								ON		
Reject XOF 2000								OFF		
★ Accept XOF 5000									ON	
Reject XOF 5000									OFF	
★ Reserved										ON
Reserved										OFF

★ Manufacture setting

Note : Please reset the bill acceptor after set the dip switch.

L77F&PL77-XOF4(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	XOF 500	XOF 500	XOF 500	XOF 500
BV2	XOF 1000	XOF 1000	XOF 1000	XOF 1000
BV3	XOF 2000	XOF 2000	XOF 2000	XOF 2000
BV4	XOF 5000	XOF 5000	XOF 5000	XOF 5000

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	ON			
Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting