

PL77/L77F-GBP4

PL77/L77F DIP SWITCHES SETTING : 1(Pulse/ccTalk/ICT104U)

Supported bill

[England] Bank of England : 5、10、20、50

[Scotland] Bank of Scotland : 5、10、20

Clydesdale Bank : 5、10

Royal Bank of Scotland : 5、10

[Northern Ireland] Bank of Ireland : 5、10

Ulster Bank : 5、10

Danske Bank:10

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / £ 5	OFF	OFF	OFF							
2 Pulses / £ 5	OFF	OFF	ON							
3 Pulses / £ 5	OFF	ON	OFF							
4 Pulses / £ 5	OFF	ON	ON							
5 Pulses / £ 5	ON	OFF	OFF							
10 Pulses / £ 5	ON	OFF	ON							
20 Pulses / £ 5	ON	ON	OFF							
100 Pulses / £ 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept £ 5						ON				
Reject £ 5						OFF				
★ Accept £ 10							ON			
Reject £ 10							OFF			
★ Accept £ 20								ON		
Reject £ 20								OFF		
★ Accept £ 50									ON	
Reject £ 50									OFF	
★ Reserved										ON
Reserved										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only used for pulse protocol.

(3) CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

PL77/L77F-GBP4(Pulse/ccTalk/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ICT104U Mode		ON	ON	
Reserved		OFF	ON	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
Pulse Mode		ON	OFF	
★ ccTalk Interface		OFF	OFF	
ICT104U Mode		ON	ON	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note: CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
★ ICT104U Mode		ON	ON	
Reserved		OFF	ON	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	£ 5	£ 5	£ 5
BV2	£ 10	£ 10	£ 10
BV3	£ 20	£ 20	£ 20
BV4	£ 50	£ 50	£ 50