

L83-BGN5

L83 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill BGN 5, 10, 20, 50, 100 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / BGN 5	OFF	OFF	OFF							
	2 Pulse / BGN 5	OFF	OFF	ON							
	3 Pulse / BGN 5	OFF	ON	OFF							
	4 Pulse / BGN 5	OFF	ON	ON							
	5 Pulse / BGN 5	ON	OFF	OFF							
	10 Pulse / BGN 5	ON	OFF	ON							
	20 Pulse / BGN 5	ON	ON	OFF							
	100 Pulse / BGN 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept BGN 5				ON						
	Reject BGN 5				OFF						
★	Accept BGN 10				ON						
	Reject BGN 10				OFF						
★	Accept BGN 20				ON						
	Reject BGN 20				OFF						
★	Accept BGN 50				ON						
	Reject BGN 50				OFF						
	Accept BGN 100				ON						
★	Reject BGN 100				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L83-BGN5(Pulse/ICT/MDB)

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104 Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	Pulse	ICT104	MDB
BV1	BGN 5	BGN 5	BGN 5
BV2	BGN 10	BGN 10	BGN 10
BV3	BGN 20	BGN 20	BGN 20
BV4	BGN 50	BGN 50	BGN 50
BV5	BGN 100	BGN 100	BGN 100

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104 Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104 Interface		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting